

RECOMMENDED ACCESSORIES

Low Pressure Fuel Solenoid Kit



Designed for the HPS series generators that will be left unattended while connected to the vapor fuel supply. The normally closed ASCO valve interrupts the fuel supply whenever the generator is not running to prevent costly and potentially dangerous fuel leaks

Two Wheel Dolly Kit



Easily maneuver your HPS series generator with an all-terrain two wheel dolly kit with flat free tires (HPS12000HE model has a 4 wheel dolly kit standard)

Emergency Transfer System (ETS)



Quickly and safely connect to your electrical panel for backup service during a power outage. Comes with hinged lockable enclosure, 12-foot cord with plug, Square D circuit breaker load center with interlocked generator and utility main breaker

Generator Cover



While your generator is not in use, protect it from the elements with our canvas cover

Trickle Battery Charger



Ensure a reliable start up every time with our three stage battery charging system

NOTE: These accessories are available individually or priced out as a kit. Please consult your local WINCO dealer for pricing. Matching 30 amp and 60 amp plugs are also available

WINCO[®]

HOME POWER GENERATORS



Contact:

MrGenerator.com

800-232-3208

**106 North Medina Street
Medina, Ohio 44256**

sales@MrGenerator.com

The convenience of a portable generator with the versatility of using multiple fuel sources, gives WINCO Home Power® Systems an upper hand over the competition.



RELIABILITY

WINCO uses premium Honda GX and Briggs & Stratton Vanguard engines. These engines have gone through each manufacturer's application reviews and maintain the full factory warranty as well as EPA certification.

CONFIDENCE

Home Power models utilize generator ends with total harmonic distortion (THD) of less than 6%, making these units safe for sensitive household loads. Our models have low oil protection to prevent damage to the engine. An optional fuel solenoid kit can be purchased to ensure unattended units will not leak gaseous fuel if the unit unexpectedly shuts down.

EXPERIENCE

WINCO Tri-Fuels have been built since 1987, making WINCO models the longest lasting Tri-Fuel line on the market today. The combination of engine, generator end, fuel demand regulator, and receptacle package have been engineered to increase the serviceability and longevity of our units.

POWERED by
HONDA



WINCO®

Tri-Fuel Portable Generators

Model	HPS6000HE*	HPS9000VE	HPS12000HE
Electrical Specifications			
Max Rating (1)	6000 watts	9000 watts	12000 watts
Cont. Rating Gasoline	5500 watts	8000 watts	10800 watts
Cont. Rating LP	N/A	7200 watts	9720 watts
Cont. Rating NG	4400 watts	6400 watts	8640 watts
Voltage	120/240	120/240	120/240
Cont. Amps (1)	45.8/22.9	66.7/33.3	90/45
Motor Starting (1)(2)	2 hp	4 hp	5 hp
Engine Data			
Make/Model	Honda GX340	B&S Vanguard	Honda GX630
Displacement	389cc	480cc	688cc
Starting System (3)	Electric/Recoil	Electric/Recoil	Electric
Fuel Tank Capacity	7 gal	7 gal	15 gal
Low Oil Protection	Standard	Standard	Standard
dba Rating @ 7 Meters	72	77	78
Fuel Consumption			
Gasoline	1.0 gal/hr	1.3 gal/hr	1.67 gal/hr
LP Vapor	N/A	1.9 gal/hr	2.2 gal/hr
Natural Gas	160 ft ³ /hr	180 ft ³ /hr	200 ft ³ /hr
Receptacles			
120V NEMA 5-20R	2-20 amp	4-20 amp	4-20 amp (GFCI)
120/240 Twistlock NEMA L14-30R	1-30 amp	1-30 amp	1-30 amp
120/240V Straight Blade NEMA 14-60R	-	-	1-60 amp
General Information			
Dimensions (in)(LxWxH)	32.75x 22.5x 22	32.75x 22.5x 22	44.7x 36x 33 (4)
Shipping Weight	224 lbs	267 lbs	460 lbs
Engine/Generator Warranty (5)	3 yr/2 yr	3 yr/2 yr	3 yr/2 yr
NOTE: (1) Based on gasoline fuel, derate 10% for LP and 20% for NG (2) Code G capacitor start motor (3) Battery NOT included, see individual spec sheets for battery requirements (4) HPS12000HE dimensions include installed wheel kit (5) Prime Power Warranty-120 days. Engine warranty administered by engine manufacturer. Contact your local Honda or B&S service center for warranty assistance. WINCO Inc. can assist in locating appropriate engine warranty support. *HPS6000HE is not certified for LP gas use.			

HOME POWER®



HPS6000HE



HPS9000VE



HPS12000HE

Contact MrGenerator.com 800-232-3208 sales@MrGenerator.com

Contact MrGenerator.com 800-232-3208 sales@MrGenerator.com